



#### **Standard Sizes**

Amperes	Size	Copper Bar
800 amp	30"x24"x12"	1/4"x3"
1000 amp	30"x24"x12"	1/4"x4"
1200 amp	30"x24"x12"	1/4"x4"
1600 amp	30"x24"x12"	1/2"x4"
2000 amp	30"x24"x12"	1/2"x4"
2500 amp	30"x24"x12"	3/4"x4"
3000 amp	30"x24"x12"	3/4"x4"

#### **NEMA 3R**

# Nema type 3r Bussed Weather Head

### **Application**

NEMA Type 3r Bussed Weather Head is designed to provide a main entry service drop. These weather heads produce ampacity ranges from 800 to 4000 amps at 600 volts.

#### Construction

Made from 12 gauge hot rolled steel and painted asa gray. Copper bars are mill plated and mounted on 3" insulators. Typical copper punching is 1 3/4" x 1 3/4", punches are 9/16" diameter. All Weather Heads are continuously welded. The covers have a gasket seal and held in place with self drilling screws.

## **Industry standards**

These screw cover enclosures conform to the standards set by the National Electrical Manufactures Association for type 3r rainproof and sleet-ice enclosures.