



22133 Old Nacogdoches Rd. New Braunfels, Tx 78132



Standard Sizes

Amperes	Size	Copper Bar
800 amp	48"x60"x30"	1/4" x 3"
1000 amp	48"x60"x30"	1/4" x 4"
1200 amp	48"x60"x30"	1/4" x 4"
1600 amp	48"x60"x30"	1/2" x 4"
2000 amp	48"x60"x30"	1/2" x 4"
2500 amp	48"x60"x30"	3/4" x 4"
3000 amp	48"x60"x30"	3/4" x 4"
3500amp	48"x60"x30"	1/2" x 6"
4000amp	48"x60"x30"	1" x 4"
1600 amp	60"x72"x30"	1/2" x 4"
2000 amp	60"x72"x30"	1/2" x 4"
2500 amp	60"x72"x30"	3/4" x 4"
3000 amp	72"x72"x30"	3/4" x 4"
3500amp	72"x72"x30"	1/2" x 6"
4000amp	72"x72"x30"	1" x 4"
5000amp	72"x72"x30"	1" x 6"

NEMA 3R

Nema type 3r Cable Tap Boxes

Application

Cable tap boxes are designed to allow distribution of large amounts of low voltage electrical power. Amperes ratings are at 600 volts.

Construction

Made from 12 gauge hot rolled steel and painted as a gray. Copper bars are mill plated and mounted on 3" insulators. Typical copper punching is 1 3/4" x 1 3/4", punches are 9/16" diameter. All tap boxes come with a 36" throat. All boxes come with one or two locking handles depending on the size of the box.

Industry standards

These screw cover enclosures conform to the standards set by the National Electrical Manufacturers Association for type 3r rainproof and sleet-ice enclosures.





