



22133 Old Nacogdoches Rd. New Braunfels, Tx 78132



## Standard Sizes

Amperes	Size	Copper Bar
800 amp	48"x60"x30"	1/4" x 3"
1000 amp	48"x60"x30"	1/4" x 4"
1200 amp	48"x60"x30"	1/4" x 4"
1600 amp	48"x60"x30"	1/2" x 4"
2000 amp	48"x60"x30"	1/2" x 4"
2500 amp	48"x60"x30"	3/4" x 4"
3000 amp	48"x60"x30"	3/4" x 4"
3500amp	48"x60"x30"	1/2" x 6"
4000amp	48"x60"x30"	1" x 4"
1600 amp	60"x72"x30"	1/2" x 4"
2000 amp	60"x72"x30"	1/2" x 4"
2500 amp	60"x72"x30"	3/4" x 4"
3000 amp	72"x72"x30"	3/4" x 4"
3500amp	72"x72"x30"	1/2" x 6"
4000amp	72"x72"x30"	1" x 4"
5000amp	72"x72"x30"	1" x 6"

## NEMA 3R

### Nema type 3r Cable Tap Boxes

#### Application

Cable tap boxes are designed to allow distribution of large amounts of low voltage electrical power. Amperes ratings are at 600 volts.

#### Construction

Made from 12 gauge hot rolled steel and painted as a gray. Copper bars are mill plated and mounted on 3" insulators. Typical copper punching is 1 3/4" x 1 3/4", punches are 9/16" diameter. All tap boxes come with a 36" throat. All boxes come with one or two locking handles depending on the size of the box.

#### Industry standards

These screw cover enclosures conform to the standards set by the National Electrical Manufacturers Association for type 3r rainproof and sleet-ice enclosures.

